



DCL20 is an induction loop kit which enables to equip reception desks or counter. This system enables to meet equal opportunity standards and to respect IEC-60118-4 standard requirements.

The amplifier is designed to be discreetly fixed under a desk or a counter. It includes two inputs, settings and LED which shows the existence of the power block and the loop power.

The provided kit includes the induction loop amplifier, a microphone, a loop, a power block and 3 « adapted for hearing-impaired area » stickers. The device includes an audio processing which enables to have an automatic sound recording level enslavement avoiding loud and sudden noises.



- Supplied with complete kit
- 2 inputs : 1 micro/line and 1 line
- Phantom power
- Power supplied
- Functioning indicator
- Output protection and control
- Small size (92x52x18mm)
- > 2A peak current capacity
- Compressor and noise blanker
- Output power mode
- Warranty : 5 years

Input	
Audio input	2 (1 micro or line input and 1 line input)
Type	Micro jack 3,5, terminal block
Phantom	4,5V 1mA
Power	
Caractéristiques	12V DC 1,5A
Type	Separated power block
Voltage	230V 50/60 Hz
Power	20W max
Fuse	Thermal
Audio processor	
Compressor	Variable 1 : 1 à 20 : 1
Etching	10mS
Lowering	Automatic 500mS or 1500mS
Noise reduction	Limited bandwidth for 8 KHz total gain, 16KHz -6dB
Dynamic	> 60dB
THD	< 0,5%

Output	
Type	Current
Loop impedance	0,1 Ohm to 1Ohm
Peak current	3,5A
RMS Power	2A à 1 KHz
Protection	Thermal, short-circuit and start
Size and weight ( mm)	
DCL20	92 x 52 x 18 (L x H x P)
Packaging	190 x 190 x 50
Weight	0,850 kg





## KIT

ACCESSORIES INCLUDED IN THE KIT	DCL20-SK Kit for counters	DCL20-E2 Kit for counter with headphones	DCL20-K1 Kit for counters with gooseneck micro	DCL20-K2 Kit for counters with handset	DCL20-TV Kit for TV rooms	DCL20-SA Kit for 50m <sup>2</sup> rooms
		<ul style="list-style-type: none"> <li>○ DCL20 amplifier</li> <li>○ Power block</li> <li>○ Surface micro</li> <li>○ Loop with RJ11 connections</li> <li>○ RJ11 adapter -&gt; Phoenix terminal block</li> <li>○ Fixing sticker clip for loop</li> <li>○ 2 « adapted for hearing-impaired area » stickers</li> </ul>	<ul style="list-style-type: none"> <li>○ DCL20 amplifier</li> <li>○ Power block</li> <li>○ Surface microphone</li> <li>○ Headhne OP-E2</li> <li>○ Loop with RJ11 connections</li> <li>○ RJ11 adapter -&gt; Phoenix terminal block</li> <li>○ Fixing sticker clip for loop</li> <li>○ 2 « adapted for hearing-impaired area » stickers</li> </ul>	<ul style="list-style-type: none"> <li>○ DCL20 amplifier</li> <li>○ Power block</li> <li>○ Gooseneck microphone</li> <li>○ Loop with RJ11 connections</li> <li>○ RJ11 adapter -&gt; Phoenix terminal block</li> <li>○ Fixing sticker clip for loop</li> <li>○ 2 « adapted for hearing-impaired area » stickers</li> </ul>	<ul style="list-style-type: none"> <li>○ DCL20 amplifier</li> <li>○ Power block</li> <li>○ Gooseneck microphone</li> <li>○ Handset</li> <li>○ Loop with RJ11 connections</li> <li>○ RJ11 adapter -&gt; Phoenix terminal block</li> <li>○ Fixing sticker clip for loop</li> <li>○ 2 « adapted for hearing-impaired area » stickers</li> </ul>	<ul style="list-style-type: none"> <li>○ DCL20 amplifier</li> <li>○ Power block</li> <li>○ Surface microphone</li> <li>○ Coil 35 m</li> <li>○ Loop with RJ11 connections</li> <li>○ RJ11 adapter -&gt; Phoenix terminal block</li> <li>○ 2 « adapted for hearing-impaired area » stickers</li> </ul>

## ACCESSORIES

### OP-M

Miniature surface microphone for DCL20 with jack 3,5.



### PS-20

12V 1 5A power block for DCL20.



### OP-IL

Replacement loop for reception desk



### OP-M02

Miniature surface microphone for DCL20 with jack 3,5.



### OP-Toslink

Coaxial Analog Optical Digital Audio Signal Adapter 5v



### OP-IL50

Coil of 50m of cable 1x0.52mm<sup>2</sup>



### OP-M80

OP-M80 is an optional microphone for proximity amplifier such as DCL20-K. It enables to provide a clear and audible sound in all situations to people with hearing-aid.



### OP-E2

Headset in handset form for DCL20



### MATLOOP

MatLoop is a 600 x 600 mm mat including a magnetic loop for hearing-impaired people who own hearing-aid with T position reception.



### OP-FSM-02

Field Strength Meter in accordance. Provided with the OP-778 headphones



### OP-WALL2

The OP-WALL2 is a rigid PVC board connected to the induction loop of your reception.

Dimensions : 170x170x12mm



### OP-CW2

Easel for OP-WALL2 and DCL20

