

HMD1.0A-TV

The HMD1.0A-TV kit is a hybrid driver that integrates a 3.5 Arms loop amplifier and an Auracast™ transmitter for rooms up to 100 m² with the standard 24 V 3 A power supply, or 150 m² with the PS-HMD32V power supply.

The kit comes with a 30-meter cable, a digital-to-analog converter, an external 24 V 3 A power supply, a surface-mounted microphone, and a “hearing-impaired-friendly zone” sticker.



Kit contents

- Phoenix connectors
- Screwdriver
- OP-M (surface microphone)
- RCA cable
- OP-IL50
- Power supply
- IEC Compliant Sticker
- OP-TOS Link

The same kit is available without the Auracast™ module

- HMD1.0-TV